

Welcome ...

EDC524 Business Edition 4.6.2	English	English
Last System Startup	CDT 05-26-2010 15:41:41	French
System Time	CDT 06-04-2010 10:22:34	Spanish
Weekday	Friday	Portuguese

Name:

Password:

1 Browser: 192.168.50.140
or designated IP address
Name: user1
Password: pw

EDC 524 Administration

- Custom Days
- Schedules
- Readers
- Access Groups
- Cards
- Persons
- Fingerprints
- Output Schedules
- Logoff

2 Persons > New Person

Parameter	Setting	Example
Person Number	<input type="text" value="12345"/>	0000001
Delete Person		
Fingerprint Number	None available	
Last Name	<input type="text" value="Pula"/>	Public
First Name	<input type="text" value="Laura"/>	John
PIN	<input type="text"/>	1234
PIN (Alarm arm/disarm)	<input type="text"/>	
PIN (Under duress)	<input type="text"/>	
Alarm Arm	<input type="checkbox"/>	
Alarm Disarm	<input type="checkbox"/>	
Open Duration	<input type="text" value="0.1 (No personal time)"/> s (0 - 9,9 10 - 99)	5
Max Open Duration	<input type="text" value="0.1 (No personal time)"/> s (0 - 9,9 10 - 99)	10
Event Alert Level	Default	
Access Group	Group 24/7	Office
Access Group Start	<input type="text"/>	01-01-2006 00:00
Access Group End	<input type="text"/>	12-31-2006 23:59
Supervisor Group	<input type="text"/>	
Supervisor Group Start	<input type="text"/>	01-01-2006 00:00
Supervisor Group End	<input type="text"/>	12-31-2006 23:59

3 Person Number: (select 5 digits)
Last Name: Employee's last name
First Name: Employee's first name
Access Group: 24/7 (Then save)

4 At Fingerprint Key reader

- Press #-9-9-# followed by 1-2-3-4-#
- Press 1-2-# followed by (unique 5-digit user ID) -# ... (i.e. 32658#)

- Place and lift new user finger three times, guided by the light
- Repeat with a second finger (from other hand)
- Press #-#-# to exit enrollment

Person Number:

First Name:

Last Name:

5 (Refresh screen)
Click on Persons > Person Number
Note: If you want to remove, click trash can, Fingerprint Number drop down (Then save)

Person Number:

Fingerprint Number:

Last Name:

First Name:

PIN:

PIN (Alarm arm/disarm):

PIN (Under duress):

Alarm Arm:

Alarm Disarm:

Open Duration: s (0 - 9,9 | 10 - 99)

Max Open Duration: s (0 - 9,9 | 10 - 99)

Event Alert Level: Default

Access Group: Group 24/7

Access Group Start:

Access Group End:

Supervisor Group:

Supervisor Group Start:

Supervisor Group End: